

REPORT

88 Series



finder[®]
SWITCH TO THE FUTURE

Multi-voltage timer

Type 88.92

Multi-voltage timer
with asymmetric
flashing function,
for front panel
or socket mounting.

Approvals (according to type)



Specification

- Multi-voltage 12 to 240 V AC/DC
- Asymmetrical flasher. ON and OFF time independently adjustable
- Time scales from 1.2 seconds to 300 hours
- 2 CO 8 A
- Front panel or plug-in using 90 Series sockets




Type 88.02.0.230.0002

- Multi-voltage 24...230 V AC/DC
- Multi-function: seven functions available
- Time scales from 0.05s to 100h
- 2 CO 8 A
- Start and Reset signals can respectively start or reset the timing period. During a Pause signal, the timing process is halted but the current output status is maintain
- LED indication of contact status
- Plug-in for use with 90 Series sockets
- Front panel mounting fixing included


- AI: On-delay
- DI: Interval
- GI: Pulse delayed
- SW: Symmetrical flasher (starting pulse on)

without control signal



- BE: Off-delay with control signal
- CE: On- and off-delay with control signal
- DE: Interval with control signal on

with control signal




Type 88.12.0.230.0002

- Multi-voltage 24...230 V AC/DC
- Multi-function: six functions available
- Time scales from 0.05s to 100h
- 2 CO 8 A
- 2 timed contacts or 1 timed + 1 instantaneous contact
- LED indication of contact status
- Plug-in for use with 90 Series sockets
- Front panel mounting fixing included

- AI a: On-delay (2 timed contacts)
- AI b: On-delay (1 timed + 1 instantaneous contact)
- DI a: Interval (2 timed contacts)
- DI b: Interval (1 timed + 1 instantaneous contact)
- GI: Pulse delayed
- SW: Symmetrical flasher (starting pulse on)

without control signal



Type 88.92.0.240.0000

Mono-function PI
Asymmetrical flasher (starting pulse OFF)


Type 88.92.0.240.0000
PI: Asymmetrical flasher (starting pulse OFF)

Type 88.92.0.240.0001

Mono-function LI
Asymmetrical flasher (starting pulse ON)

Type 88.92.0.240.0001
LI: Asymmetrical flasher (starting pulse ON)

without control signal



- Multi-voltage 12...240 V AC/DC
- Time scales from 1.2 seconds to 300 hours
- 2 CO 8 A
- LED indication of contact status
- Plug-in for use with 90 Series sockets
- Front panel mounting fixing included